

Таблица выбора.

KW	TYPE	l	N ₂ (r/min)	M ₂ (N.M)	
0.06KW	RV025	7.5	186	2.6	
	RV030				
	RV025	10	140	3.4	
	RV030				
	RV025	15	94	4.9	
	RV030			4.8	
	RV025	20	70	6.1	
	RV030			5.5	
	RV030	25	56	7.2	
	RV025	30	47	8.2	
	RV030				
	RV025	40	35	10	
	RV030			8.5	
	RV025	50	28	12	
	RV030			11.6	
	RV040			12.4	
	RV025	60	24	14	
	RV030			12.8	
RV040	12.6				
RV030	80	18	13.8		
RV040			16.8		
RV040	100	14	19.5		
0.09KW	RV025	7.5	186	3.9	
	RV030			4.0	
	RV025	10	140	5.1	
	RV030				
	RV025	15	94	7.3	
	RV030			7.2	
	RV025	20	70	9.2	
	RV030			8.3	
	RV030	25	56	10.7	
	RV025	30	47	12	
	RV030			12.3	
	RV025	40	35	15	
	RV030			12.8	
	RV030	50	28	17.4	
	RV040			18.6	
	RV030	60	24	19.2	
	RV040			19.0	
	RV040	80	18	25.2	
RV040	100	14	29.3		
0.12KW	RV030	7.5	186	5.3	
	RV040			5.3	
	RV030	10	140	6.8	
	RV040			8.9	
	RV030	15	94	9.6	
	RV040			9.9	
	RV030	20	70	11.0	
	RV040			13.0	
	RV030	25	56	14.3	
	RV040			15.1	
	0.12KW	RV030	30	47	16.4
		RV040			16.6
RV030		40	35	17.0	
RV040				21.9	
RV050		50	28	22.7	
RV030				23.2	
RV040				24.7	
RV050		60	24	26.0	
RV040				25.3	
RV050		80	18	26.2	
RV040				33.6	
RV050		100	14	34.7	
RV040				39.0	
RV050		7.5	186	39.6	
RV040				7.9	
0.18KW		RV030	10	140	7.9
		RV040			7.9
		RV030	15	94	10.2
		RV040			10.3
		RV030	20	70	14.4
		RV040			14.8
		RV030	25	56	16.5
		RV040			19.5
		RV030	30	47	21.5
	RV040	22.7			
	RV030	40	35	24.6	
	RV040			24.9	
	RV050	50	28	32.8	
	RV040			34.0	
	RV050	60	24	37.1	
	RV040			39.0	
	RV050	80	18	37.9	
	RV040			39.2	
RV050	100	14	52.1		
RV040			59.3		
0.25KW	RV040	7.5	186	11.0	
	RV050			11.2	
	RV040	10	140	14.3	
	RV050			14.5	
	RV040	15	94	20.6	
	RV050			20.7	
	RV040	20	70	27.0	
	RV050			27.5	
	RV040	25	56	31.5	
	RV050			32.8	
	RV040	30	47	34.6	
	RV050			36.4	
	RV040	40	35	45.6	
	RV050			47.3	
	RV050	50	28	54.1	
	RV050			54.5	
	RV050	80	18	72.4	
	RV063			76.7	
RV063	100	14	82.8		

Мотор-редукторы серии RV

KW	TYPE	i	N ₂ (r/min)	M ₂ (N.M)	
0.37KW	RV040	7.5	186	16.3	
	RV050			16.6	
	RV040	10	140	21.2	
	RV050			21.5	
	RV040	15	94	30.5	
	RV050			30.6	
	RV040	20	70	40.0	
	RV050			40.7	
	RV040	25	56	46.6	
	RV050			48.7	
	RV040	30	47	51.2	
	RV050			53.8	
	RV050	40	35	67.0	
	RV063			72.3	
	RV050	50	28	80.1	
	RV063			83.3	
	RV050	60	24	80.6	
	RV063	60	24	86.5	
RV063	80	18	113.5		
RV063	100	14	122.6		
0.55KW	RV050	7.5	186	24.3	
	RV050			24.6	
	RV050	10	140	31.5	
	RV050			32.0	
	RV050	15	94	45.3	
	RV063			45.5	
	RV050	20	70	60.5	
	RV063			61.6	
	RV050	25	56	72.3	
	RV063			73.2	
	RV050	30	47	80.0	
	RV063			83.3	
	RV050	40	35	104.0	
	RV063			107.5	
	RV075	50	28	115.7	
	RV063			123.9	
	RV075	60	24	144.3	
	RV063			128.6	
	RV075	80	18	156.5	
	RV075			215.8	
	RV075	100	14	235.0	
	0.75KW	RV050	7.5	186	33.6
		RV063			33.8
		RV050	10	140	43.6
RV063		44.5			
RV050		15	94	62.0	
RV063				63.7	
RV050		20	70	82.4	
RV063				84.0	
RV063		25	56	99.8	
RV063				113.6	
RV075		30	47	124.4	
RV063				146.6	
RV075		40	35	157.8	

KW	TYPE	i	N ₂ (r/min)	M ₂ (N.M)
0.75KW	RV075	50	28	196.8
	RV090			186.1
	RV075	60	24	213.4
	RV090			211.9
RV090	80	18	261.1	
RV090	100	14	292.7	
1.1KW	RV063	7.5	186	49.6
	RV075			51.4
	RV063	10	140	65.3
	RV075			67.8
	RV063	15	94	93.5
	RV075			98.6
	RV063	20	70	123.2
	RV075			127.7
	RV063	25	56	146.4
	RV075			159.2
	RV063	30	47	166.7
	RV075			182.5
	RV075	40	35	231.4
	1.1KW	RV090	40	35
RV090		50	28	272.9
RV090		60	24	310.8
RV110				319.1
RV110		80	18	403.8
RV110		100	14	471.2
1.5KW	RV063	7.5	186	67.6
	RV075			70.1
	RV063	10	140	89.1
	RV075			92.5
	RV063	15	94	127.5
	RV075			134.5
	RV063	20	70	167.9
	RV075			174.1
	RV075	25	56	217.1
	RV090			211.0
	RV075	30	47	248.9
	RV090			247.1
	RV090	40	35	313.3
	RV090			372.1
RV110	50	28	392.9	
RV090	60	24	423.8	
RV110			435.1	
RV110	80	18	550.7	
RV130			534.0	
RV130	100	14	672.2	
2.2KW	RV075	7.5	186	102.8
	RV090			101.9
	RV110	10	140	101.8
	RV075			135.7
	RV090	15	94	134.8
	RV110			133.7
	RV075	20	70	197.3
	RV090			196.7
	RV110	25	56	192.7
	RV090			254.9
	RV110	30	47	254.5
	RV090			309.5
	RV110	40	35	319.2
	RV090			362.4
RV110	354.5			

Мотор-редукторы серии RV

KW	TYPE	i	n ₂ (r/min)	M ₂ (N.M)
2.2KW	RV110	40	35	465.8
	RV110			576.2
	RV130	50	28	568.7
	RV150			570
	RV110	60	24	638.1
	RV130			655.6
	RV150			657
	RV130	80	18	783.1
	RV150			816
	RV130	100	14	985.9
RV150	960			
3.0KW	RV075	7.5	186	140.1
	RV090			139.0
	RV110			138.8
	RV075	10	140	185.0
	RV090			183.8
	RV110			182.3
	RV075	15	94	269.0
	RV090			268.2
	RV110			262.7
	RV090	20	70	347.7
	RV110			347.0
	RV090	25	56	422.0
	RV110	25	56	435.3
	RV090	30	47	494.1
	RV110			483.3
	RV110	40	35	635.1
	RV130			637.6
	RV110	50	28	785.8
	RV130			775.5
	RV150			777
RV130	60	24	894.0	
RV150			896	
RV150	80	18	1113	
RV150	100	14	1310	
4.0KW	RV075	7.5	186	186.8
	RV090			185.3
	RV110			185.0
	RV130			187.1
	RV090	10	140	245.1
	RV110			243.1
	RV130			243.1
	RV090	15	94	357.7
	RV110			350.3
	RV130			354.3
	RV090	20	70	463.5
	RV110			462.7
	RV130			469.3
	RV110	25	56	580.4
	RV130			576.4
	RV110	30	47	644.5
	RV130			652.6
	RV130	40	35	850.1
	RV130	50	28	1034.0
	RV150			1036

KW	TYPE	i	n ₂ (r/min)	M ₂ (N.M)
4.0KW	RV130	60	24	1192.0
	RV150			1195
	RV150	80	17.5	1484
5.5KW	RV110	7.5	186	254.4
	RV130			257.2
	RV110	10	140	334.3
	RV130			334.3
	RV110	15	94	481.6
	RV130			487.2
	RV110	20	70	636.2
	RV130			645.2
	RV150			645
	RV130	25	56	792.5
	RV150			788
	RV130	30	47	897.3
RV150	934			
RV130	40	35	1168.9	
RV150			1171	
RV150	50	28	1426	
RV150	60	24	1643	
7.5KW	RV110	7.5	186	346.9
	RV130			350.8
	RV110	10	140	455.8
	RV130			455.8
	RV130	15	94	664.8
	RV130	20	70	879.9
	RV150			880
	RV130	25	56	1080.7
	RV150			1074
	RV150	30	47	1274
RV150	40	35	1596	
11KW	RV150	7.5	186	512
	RV150	10	140	675
	RV150	15	94	990
	RV150	20	70	1291
15KW	RV150	25	56	1576
	RV150	7.5	186	698
	RV150	10	140	921
	RV150	15	94	1351
	RV150	20	70	1760