

Таблица выбора.

Мощность двигателя, (кВт)	Обороты выходного вала (об/мин)	Момент на выходном валу (Нм)	Сервис-фактор	Передаточное число	Тип мотор-редуктора	Двигатель IEC	Радиальная нагрузка (Н)		
0.09	12.0	47	1.3	75	PCRВ 063/040	63В6	3283		
	10.0	51	1.4	90			3488		
	7.5	62	1.1	120			3490		
	6.0	72	0.8	150			3490		
	5.0	79	0.7	180			3490		
	6.0	73	1.6	150			4840		
	5.0	81	1.3	180	PCRВ 063/050		4840		
	3.8	94	0.9	240			4840		
	3.0	106	0.7	300			4840		
	3.8	99	1.7	240	PCRВ 063/060		6270		
	3.0	109	1.4	300			6270		
	0.12	18.7	42	1.2	75		PCRВ 063/040	63А4	2833
15.6		46	1.2	90	3011				
11.7		57	0.9	120	3314				
9.3		66	0.7	150	3490				
7.8		74	0.6	180	3490				
12.0		62	1.0	75	PCRВ 063/040	63С6			3283
10.0		68	1.1	90			3488		
7.5		83	0.8	120			3490		
9.3		68	1.3	150	PCRВ 063/050	63А4	4840		
7.8		75	1.1	180			4840		
5.8		88	0.8	240			4840		
4.7		98	0.7	300	PCRВ 063/050	63С6	4840		
12.0		63	1.7	75			4506		
10.0		70	2.1	90			4788		
7.5		84	1.5	120			4840		
6.0		97	1.2	150			4840		
5.0		108	1.0	180			4840		
3.8		125	0.7	240			4840		
5.8		92	1.5	240			PCRВ 063/063	63А4	6270
4.7		103	1.2	300					6270
6.0		101	2.1	150			PCRВ 063/063	63С6	6270
5.0		112	1.8	180	6270				
3.8		131	1.3	240	6270				
3.0		145	1.0	300	6270				
18.7		64	0.8	75	PCRВ 063/040	63В4			2833
15.6		70	0.8	90			3011		
11.7	85	0.6	120	3314					
18.7	64	1.4	75	PCRВ 063/050	3889				
15.6	71	1.5	90		4132				
11.7	87	1.1	120		4548				
9.3	101	0.9	150		4840				
7.8	113	0.7	180		4840				
5.8	133	0.6	240		4840				
12.0	95	1.2	75				4506		

Мотор-редукторы серии RV



0.18	10.0	105	1.4	90	PCRV 071/050	71A6	4788	
	7.5	126	1.0	120			4840	
	9.3	103	1.7	150	PCRV 063/063	63B4	6270	
	7.8	117	1.4	180			6270	
	5.8	139	1.0	240			6270	
	4.7	155	0.8	300			6270	
	12.0	97	2.2	75	PCRV 071/063	71A6	5889	
	10.0	107	2.4	90			6259	
	7.5	131	1.8	120			6270	
	6.0	152	1.4	150			6270	
	5.0	168	1.2	180			6270	
	3.8	197	0.9	240			6270	
	3.0	218	0.7	300			6270	
	5.0	179	1.7	180			7380	
	3.8	211	1.2	240	PCRV 071/075	71A6	7380	
	3.0	235	1.0	300			7380	
0.25	18.7	88	1.0	75	PCRV 071/050	71A4	3889	
	15.6	98	1.1	90			4132	
	11.7	121	0.8	120			4548	
	18.7	91	1.8	75	PCRV 071/063		71A4	5083
	15.6	100	2.0	90				5401
	11.7	125	1.5	120				5945
	9.3	143	1.2	150				6270
	7.8	163	1.0	180				6270
	5.8	192	0.7	240				6270
	4.7	215	0.6	300	6270			
	12.0	135	1.6	75	PCRV 071/063	71B6	5889	
	10.0	148	1.8	90			6259	
	7.5	181	1.3	120			6270	
	6.0	211	1.0	150	6270			
	9.3	151	1.7	150	PCRV 071/075	71A4	7380	
	7.8	172	1.4	180			7380	
	5.8	201	1.1	240			7380	
	4.7	230	0.9	300			7380	
	12.0	139	2.4	75		71B6	6952	
	10.0	155	2.5	90			7380	
	7.5	191	1.9	120			7380	
	6.0	219	1.5	150			7380	
	5.0	248	1.2	180	7380			
	5.0	263	1.9	180	8180			
	3.8	318	1.4	240	PCRV 071/090	71B6	8180	
	3.0	358	1.1	300			8180	
0.37	18.7	134	1.2	75	PCRV 071/063	71B4	5083	
	15.6	148	1.4	90			5401	
	11.7	185	1.0	120			5945	
	9.3	212	0.8	150			6270	
	18.7	138	1.8	75	PCRV 071/075		6000	
	15.6	154	1.9	90			6375	
	11.7	191	1.5	120			7017	
	9.3	223	1.1	150			7380	

Мотор-редукторы серии RV



0.37	7.8	254	0.9	180	PCRВ 071/075	71В4	7380		
	12.0	206	1.6	75	PCRВ 080/075	80А6	6952		
	10.0	230	1.7	90			7380		
	7.5	283	1.3	120			7380		
	6.0	324	1.0	150			7380		
	7.8	268	1.5	180			PCRВ 071/090	71В4	8180
	5.8	321	1.1	240	8180				
	4.7	371	0.9	300	8180				
	6.0	347	1.6	150	PCRВ 080/090	80А6	8180		
	5.0	389	1.3	180			8180		
	3.8	471	1.0	240			8180		
	3.8	509	1.6	240			PCRВ 080/110	80А6	10320
	3.0	577	1.3	300	10320				
	0.55	18.7	200	0.8	75	PCRВ 071/063	80А4	5083	
15.6		219	0.9	90	PCRВ 071/075	5401			
18.7		205	1.2	75		6000			
15.6		230	1.3	90		6375			
11.7		284	1.0	120		7017			
18.7		205	1.2	75		6000			
15.6		230	1.3	90		6375			
11.7		284	1.0	120		7017			
9.3		332	0.8	150		7380			
12.0		306	1.1	75		80А6		6952	
10.0		341	1.1	90				7380	
15.6		240	2.3	90		PCRВ 080/090		80А4	7054
11.7		297	1.6	120					7764
9.3		355	1.3	150					8180
7.8		398	1.0	180			8180		
10.0		357	2.0	90	80В6		8174		
7.5		441	1.4	120			8180		
6.0		516	1.1	150			8180		
5.0		578	0.9	180			8180		
7.8		425	1.8	180			PCRВ 080/110	80А4	10320
5.8		513	1.3	240					10320
4.7		597	1.0	300	10320				
7.5		462	2.6	120	80В6	10320			
6.0		552	2.0	150		10320			
5.0		620	1.6	180		10320			
3.8		756	1.1	240		10320			
3.8		756	1.6	240		PCRВ 080/130		13500	
3.0		858	1.3	300				13500	
0.75		18.7	280	0.9		75		PCRВ 080/075	80В4
		15.6	313	1.0	90	PCRВ 080/090	6375		
	15.6	327	1.7	90	7054				
	11.7	405	1.2	120	7764				
	9.3	483	0.9	150	8180				
	7.8	543	0.7	180	8180				
	11.7	430	2.2	120	PCRВ 080/110	9811			
	9.3	506	1.7	150		10320			
	7.8	580	1.3	180		10320			

Мотор-редукторы серии RV



0.75	5.8	700	0.9	240	PCRВ 080/110	80В4	10320
	12.4	393	3.2	73	PCRВ 090/110	90S6	9614
	9.3	508	2.3	96.8			10320
	7.4	607	1.8	121			10320
	6.2	682	1.5	145.2			10320
	4.6	832	1.0	193.6			10320
	5.8	712	1.4	240			PCRВ 080/130
	4.7	813	1.1	300	PCRВ 090/130	90S6	13500
	12.4	399	4.4	73			12575
	9.3	508	3.2	96.8			13500
	7.4	607	2.6	121			13500
	6.2	682	2.1	145.2			13500
	4.6	832	1.5	193.6			13500
	3.7	944	1.2	242			13500
1.1	12.4	576	2.2	73	PCRВ 090/110	90L6	9614
	9.3	746	1.6	96.8			10320
	7.4	890	1.2	121			10320
	6.2	1000	1.0	145.2			10320
	19.3	392	2.5	73		90S4	8298
	14.5	508	1.8	96.8			9133
	11.6	599	1.5	121			9838
	9.6	686	1.1	145.2			10320
	7.2	828	0.8	193.6			10320
	12.4	585	3.0	73	PCRВ 090/130	90L6	12575
	9.3	746	2.2	96.8			13500
	7.4	890	1.7	121			13500
	6.2	1000	1.4	145.2			13500
	4.6	1220	1.0	193.6		13500	
	19.3	398	3.5	73		90S4	10853
	14.5	508	2.6	96.8			11945
	11.6	608	2.0	121			12868
	9.6	686	1.6	145.2			13500
7.2	843	1.2	193.6	13500			
5.8	962	0.9	242	13500			
1.5	19.3	535	1.9	73	PCRВ 090/110	90L4	8298
	14.5	693	1.3	96.8			9133
	11.6	817	1.1	121			9838
	9.6	936	0.8	145.2			10320
	19.3	542	2.6	73	PCRВ 090/130		10853
	14.5	693	1.9	96.8			11945
	11.6	830	1.5	121			12868
	9.6	936	1.1	145.2			13500
	7.2	1149	0.8	194			13500
2.2	38.6	398	2.1	73	PCRВ 090/110	90L2	6586
	28.9	516	1.5	96.8			7249
	23.1	617	1.2	121			7809
	38.6	409	2.9	73	PCRВ 090/130		8614
	28.9	545	2.0	96.8			9481
	23.1	654	1.6	121			10213
	19.3	752	1.3	145.2			10853